

# Small Instrumentation Modules

## SIM964 — 1 MHz analog limiter

- **Settable upper & lower limits ( $\pm 10$  V)**
- **10 mV resolution**
- **1 MHz bandwidth**
- **TTL outputs for limit detecting**
- **High slew rate**



### SIM964 Analog Limiter

The SIM964 Analog Limiter provides upper and lower voltage limits for conditioning dynamic signals. Limits are set between  $\pm 10$  V with 10 mV resolution. Two rear-panel TTL signals are activated when upper or lower limits are exceeded. The SIM964 uses SRS's clock-stopping architecture design to eliminate digital noise artifacts. The low output noise and low harmonic distortion of the SIM964 make it ideal for many applications.

#### Specifications

Limit settings	$\pm 10$ V (both upper and lower)
Resolution	10 mV
Bandwidth	1 MHz
Limit type	Soft limit (100 mV range)
Input impedance	1 M $\Omega$
Output noise	<400 $\mu$ Vrms
THD	0.01 % (80 dB) at 1 kHz
Slew rate	20 V/ $\mu$ s

Limit detect	TTL level signals (rear-panel BNC connectors) are high when upper or lower limits are exceeded.
Operating temperature	0 °C to 40 °C, non-condensing
Interface	Serial via SIM interface
Connectors	BNC (2 front, 2 rear) DB15 (male) SIM interface
Power	+5 VDC (100 mA max.), $\pm 15$ VDC (300 mA max.)
Dimensions	1.5" $\times$ 3.6" $\times$ 7.0" (WHD)
Weight	1.5 lbs.
Warranty	One year parts and labor on defects in materials and workmanship

#### Ordering Information

SIM964 Programmable analog limiter